

Phase Shifter, X-Band, 6-Bit 8 - 12 GHz



CGY2172XBUH/C1

Rev. V1

Features

- Insertion Loss: 8 dB at 10 GHz
- Phase Shift Range: 360°
- RMS Phase Error: 2° @ 10 GHz
- Input P1dB: 18 dBm
- Return Loss: 17 dB @ 10 GHz (All states)
- 0 / 5 V Control Lines
- Chip Size: 3900 x 1300 $\mu\text{m} \pm 5 \mu\text{m}$
- Tested, Inspected Known Good Die (KGD)
- Samples Available
- Demonstration Boards Available
- Space and MIL-STD Available
- RoHS* Compliant

Applications


- Radar
- Telecommunication
- Instrumentation

Description

The CGY2172XBUH/C1 is a high performance GaAs MMIC 6-bit phase shifter operating in X-band. This device has a nominal phase shifting range of 0 - 360° in 5.625° steps and uses an optimum combination of switched line and high pass/low pass filters to obtain very low phase error and insertion loss variations. It covers the frequency range of 8 to 12 GHz.

The die is manufactured using 0.18 μm gate length pHEMT technology. The MMIC uses gold bond pads and backside metallization and is fully protected with Silicon Nitride passivation to obtain the highest level of reliability. This technology has been evaluated for Space applications and is on the European Preferred Parts List of the European Space Agency.

Block Diagram



Ordering Information

Part Number	Package
CGY2172XBUH/C1	DIE

* Restrictions on Hazardous Substances, compliant to current RoHS EU directive.

Electrical Specifications:
Measured On Wafer, Freq. = 10 GHz, V_{SS} = -5 V, I_{SS} = 8 mA, T_A = +25°C

Parameter	Test Conditions	Units	Min.	Typ.	Max.
Insertion Loss	—	dB	—	8	—
Noise Figure	@ Reference State	dB	—	8	—
Phase Range	—	°	—	360	—
Input & Output Return Loss	@ RF1 & RF2	dB	—	17	—
RMS Phase Error vs. Phase Setting ¹	—	°	—	2	—
Maximum Phase Error vs. Phase Setting	—	dB	—	±5	—
RMS Attenuation Variation with Phase Setting ¹	—	dB	—	0.2	—
Maximum Attenuation Variation with Phase Setting	—	dB	—	±0.4	—
P1dB	—	dBm	—	18	—

1. The RMS value is the root mean square of the error defined as below:
Where x_i is the difference between the measured value and the expected value.

$$x_{\text{rms}} = \sqrt{\frac{1}{N} \sum_{i=1}^N x_i^2} = \sqrt{\frac{x_1^2 + x_2^2 + \dots + x_N^2}{N}}$$

Absolute Maximum Ratings^{2,3}

Parameter	Absolute Maximum
Phase Control Inputs	0 to +7 V
Source Supply Voltage	-7 to 0 V
Input Power	TBD dBm
Junction Temperature	+150°C
Operating Temperature	-40°C to +85°C
Storage Temperature	-55°C to +150°C

2. Exceeding any one or combination of these limits may cause permanent damage to this device.
3. MACOM does not recommend sustained operation near these survivability limits.

Handling Procedures

Please observe the following precautions to avoid damage:

Static Sensitivity

These electronic devices are sensitive to electrostatic discharge (ESD) and can be damaged by static electricity. Proper ESD control techniques should be used when handling these devices.

Phase Shifter, X-Band, 6-Bit 8 - 12 GHz



CGY2172XBUH/C1

Rev. V1

Logic Truth Table

	A0	A1	A2	A3	A4	A5
Nominal Phase Shift	-5.625°	-11.25°	-22.5°	-45°	-90°	-180°
Pad	P5	P11	P22	P45	P90	P180
Phase Shift Activated	+5 V	+5 V	+5 V	+5 V	+5 V	+5 V
Reference State	0 V	0 V	0 V	0 V	0 V	0 V

Logic Truth Table (V)

	A5	A4	A3	A2	A1	A0
Phase Shift (°)	-180°	-90°	-45°	-22°	-11°	-5°
0	0	0	0	0	0	0
-5.625	0	0	0	0	0	1
-11.25	0	0	0	0	1	0
-22.5	0	0	0	1	0	0
-45	0	0	1	0	0	0
-61	0	0	1	0	1	1
-90	0	1	0	0	0	0
-180	1	0	0	0	0	1
-270	1	1	0	0	0	0
-354	1	1	1	1	1	1

Control Voltage

State	Min.	Typ.	Max.	Unit
Low (0)	-0.01	0	+0.01	V
High (1)	4.75	5.00	5.25	V






Phase Shifter, X-Band, 6-Bit 8 - 12 GHz






CGY2172XBUH/C1

Rev. V1




Typical Performance Curves:



Typical Performance Curves:



Typical Performance Curves:




Phase Shifter, X-Band, 6-Bit 8 - 12 GHz



CGY2172XBUH/C1


Rev. V1

Bonding Diagram & Assembly Information:



RF interface : coplanar or microstrip, bonding $\approx 400/500 \mu\text{m}$.

Mechanical Information:



Chip Size = 3900 x 1300 μm (± 5 μm)
 DC Pads = 100 x 100 μm, spacing = 150 μm, top metal = Au
 RF Pads = 85 x 150 μm, top metal = Au
 Chip Thickness = 100 μm

Pad Position⁴

Pad Name	Symbol	Coordinate		Description
		X	Y	
P1	RF1	105	882	RF Port 1
P2	RF2	3760	882	RF Port 2
REF	REF	1412	112	Output Voltage Reference (do not connect)
P5	A0	1562	112	5° cell control
P11	A1	1712	112	11° cell control
P22	A2	1862	112	22° cell control
P45	A3	2012	112	45° cell control
P90	A4	2162	112	90° cell control
P180	A5	2312	112	180° cell control
VSS	VSS	2462	112	Negative Supply Voltage
GND	GND	2612	112	Ground (back side)

4. X=0, Y=0 at bottom left corner. See Mechanical Information for more details.

MACOM Technology Solutions Inc. ("MACOM"). All rights reserved.

These materials are provided in connection with MACOM's products as a service to its customers and may be used for informational purposes only. Except as provided in its Terms and Conditions of Sale or any separate agreement, MACOM assumes no liability or responsibility whatsoever, including for (i) errors or omissions in these materials; (ii) failure to update these materials; or (iii) conflicts or incompatibilities arising from future changes to specifications and product descriptions, which MACOM may make at any time, without notice. These materials grant no license, express or implied, to any intellectual property rights.

THESE MATERIALS ARE PROVIDED "AS IS" WITH NO WARRANTY OR LIABILITY, EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, INFRINGEMENT OF INTELLECTUAL PROPERTY RIGHT, ACCURACY OR COMPLETENESS, OR SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES WHICH MAY RESULT FROM USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.